

Optical Holonomic Quantum Computation*

Demosthenes Ellinas¹ and Jiannis Pachos²

¹*Technical Univeristy of Crete, Department of Sciences, Section of Mathematics, GR-73 100 Chania Crete Greece, ellinas@science.tuc.gr*

²*Max Planck Institut für Quantenoptik D-85748 Garching, Germany, jip@mpq.mpg.de*

Holonomic quantum computation (HQC) is materialized here with quantum optics components. Holonomies are the generalization of the Berry phases to unitary matrices with dimensionality the same as the degree of degeneracy of the system. In a nonlinear Kerr medium the degenerate states of laser beams are interpreted as qubits. Control manipulations with displacers, squeezers and two-mode interfering devices performed in a cyclic, adiabatic fashion produce holonomies. Here, they are employed as logical gates for our HQC proposal. The effects of errors from imperfect control of classical parameters, the looping variation of which builds up holonomic gates, are investigated.

©1999 Optical Society of America

OCIS codes:(999.9999) Quantum Computing

Quantum computers consist of a tensor product structure of two level quantum sub-systems (qubits) which are manipulated coherently with a large set of external operations (logical gates). Here an application of holonomic manipulations [1] (see also [2]) with optical components of laser Fock states is described. Holonomy is the generalization of the well known Berry phase to the case of a higher dimensional unitary matrix [3]. It is produced by an adiabatic cyclic evolution of external control parameters that drive a degenerate Hamiltonian [4]. This Hamiltonian in our case is produced by a Kerr medium through which the lasers are passing [5]. Hence, a two fold degeneracy is created, where each qubit is encoded. As the first part of this presentation shows the logical gates are constructed by employing displacings and squeezings of each mode for producing one-qubit gates. Two-qubit gates are produced by two mode interfering devices like two-mode displacing or squeezing. Each laser encodes one qubit in its degenerate sub-space, spanned by the Fock states $|0\rangle$ and $|1\rangle$. By alternative manipulations with the displacing operator $D(\lambda) = \exp(\lambda a^\dagger - \bar{\lambda}a)$ and the squeezing operator $S(\mu) = \exp(\mu a^{\dagger 2} - \bar{\mu}a^2)$ in an adiabatic fashion it is possible to generate any one-qubit rotation. Adiabaticity along the cyclic evolution of the parameters $\lambda = x + iy$ and $\mu = r_1 \exp i\theta_1$ guarantees that the states $|0\rangle$ and $|1\rangle$ will not mix with the rest of the Fock states of the laser. On the other hand as they have the same energy they are allowed to exchange population along this cyclic evolution. The exact evolution they undertake at the end of this manipulation is given by unitaries which depend on the geometrical characteristics of the cyclic procedure [3]. The coordinates of the space where the loops belong are not abstract theoretical objects but rather the parameters the experimentalist is tuning in the lab, like the squeezing or the displacing amplitude. For a loop C_I on the $(x, r_1)_{\theta_1=0}$ plane we obtain the holonomy

$$\Gamma_A(C_I) = \exp(-i\sigma_1 \Sigma_I) , \quad (1)$$

where $\Sigma_I := \int_{D(C_I)} dx dr_1 2e^{-2r_1}$. Hence it represents the area on a hyperbolic surface enclosed by the loop C_I . For this procedure displacings and squeezings are alternated. Similarly we obtain for a loop C_{II} on $(x, r_1)_{\theta_1=\pi/2}$ the holonomy

$$\Gamma(C_{II}) = \exp(-i\sigma_2 \Sigma_{II}) \quad (2)$$

with $\Sigma_{II} := \int_{D(C_{II})} 2e^{-2r_1}$.

For the case of two-qubit gates we use two laser beams passing through a Kerr medium. This produces a 4-dimensional degenerate space with a tensor product structure. Two-mode interfering devices produce two-mode displacing transformation $N(\xi) = \exp(\xi a_1^\dagger a_2 - \bar{\xi} a_1 a_2^\dagger)$ or two-mode squeezing $M(\zeta) = \exp(\zeta a_1^\dagger a_2^\dagger - \bar{\zeta} a_1 a_2)$. Interchanging these procedures in a cyclic, adiabatic fashion produces two-qubit unitaries. In particular, for $\zeta = r_2 e^{i\theta_2}$ and $\xi = r_3 e^{i\theta_3}$ we have a four-parameter real manifold. Taking a loop $C_{III} \in (r_2, r_3)_{\theta_2=\theta_3=0}$ we obtain

*ICQI 2001 - International Conference on Quantum Information, Rochester, June 10-13, 2001 (Contribution given by D. E)

$$\Gamma(C_{III}) = \exp(-i\sigma^{12}\Sigma_{III}) \quad (3)$$

with $\Sigma_{III} := \int_{D(C_{III})} dr_2 dr_3 2 \sinh(2r_2)$. This is a nontrivial unitary transformation and hence, together with the general one-qubit holonomic transformations they can produce any desired logical gate resulting to universality. Moreover, the ability to produce a big variety of gates by simply changing the experimental parameters and spanning different loops reduces the amount of resources needed to construct certain gates in the traditional way by the successive combination of basic gates.

In the previously proposed setup the degeneracy has to be present at all times. To achieve this along with the implementation of the adiabatic transformations with the control devices it is necessary to employ the “kicking” method. The laser beams are inserted into the nonlinear Kerr medium for time Δt and alternated with infinitesimal transformation $D(\delta\lambda)$, $S(\delta\mu)$, $M(\delta\zeta)$ or $N(\delta\xi)$ which take place in times $\delta t \ll \Delta t$. This ensures the presence of the degeneracy along the adiabatic evolution.

Holonomic quantum computation is an all geometric setup of quantum evolution. The parameters of the gates are areas of particular surfaces. Deformations of these contours due to statistical experimental errors does not change the value of the areas to the first order of approximation. Moreover, the weight factors in the parameters Σ_I and Σ_{II} of the corresponding gates are exponentially decreasing for large r_1 . This makes the gates resilient to displacing control errors as they are suppressed exponentially due to squeezing [5]. Such characteristics are important for error avoiding computation.

Next we aim to discuss the error avoiding features of the optical holonomic proposal in the presence of systematic errors. More specifically the parametric loops producing holonomies, when subject to imperfections while spanned, introduce an error in the final gates through their accordingly fluctuated parameters. This is systematically studied for the Hadamard (H) gate and a non trivial two qubit gate. In order to study the errors introduced by imperfect control of the external parameters we adopt an imperfectly spanned loop, C' [6]. This by its turn will produce an area as a gate parameter given by $\Sigma' = \Sigma + \epsilon$. If the errors are statistical rather than systematic then the area spanned by this loop are, to the first order, zero. Let us consider how systematic errors in the area effect one and two qubit gates. The Hadamard gate is given by

$$U_H = \begin{bmatrix} \cos \Sigma & \sin \Sigma \\ \sin \Sigma & -\cos \Sigma \end{bmatrix}, \quad (4)$$

for $\Sigma = \pi/4$. Up to a corrective phase it may be produced by a loop C_{II} , with spanning area given by $\Sigma = \int_{D(C_{II})} dx dr_1 2e^{-2r_1}$ with $D(C_{II})$ taken to be a rectangular surface enclosed by $\{0 \leq x \leq \pi/4, 0 \leq r_1 \leq \ln 2\}$. Introduce an error in this surface by translating the borders of x and r_1 by α and β respectively, where $\alpha, \beta \ll 1$. This is a kind of systematic error. The imperfect Hadamard gate is given to the first order in ϵ by $U_H(\epsilon) = U_H + \epsilon h$, with $h = \frac{1}{\sqrt{2}} \begin{bmatrix} -1 & 1 \\ 1 & 1 \end{bmatrix}$. For large values of r_1 the dependence of ϵ on β is exponentially small, while the error of x is introduced linearly, i.e. $\epsilon = \alpha$. As the squeezing of the light beam is much harder to perform and to control in experiments compared to its displacing the above feature is very appealing. Theoretically this characteristic makes the passage from the geometrical to the topological quantum computation as β errors in the spanning of the loop C' are suppressed even if they are very large [7].

For a two qubit gate we perform a loop C_{III} between the variables r_2 and r_3 with area $\Sigma_{III} = \frac{\pi}{4}$ which eventually gives the gate

$$U = \frac{1}{\sqrt{2}} \begin{bmatrix} \sqrt{2} & 0 & 0 & 0 \\ 0 & 1 & -1 & 0 \\ 0 & 1 & 1 & 0 \\ 0 & 0 & 0 & \sqrt{2} \end{bmatrix} \quad (5)$$

Allowing the area Σ_{II} to be enclosed by the following rectangular $\{0 \leq r_2 \leq \text{arccosh}(2), 0 \leq r_3 \leq \pi/8\}$ then systematic small errors in the definition of the borders of the rectangular of the form (α', β') gives an error in the gate parameter of the form $\Sigma' = \Sigma + \delta$ with $\delta = 1.7\alpha' + \beta'$. The gate in this case is given by $U(\delta) = U + \delta u$ where

$$u = \frac{1}{\sqrt{2}} \begin{bmatrix} 0 & 0 & 0 & 0 \\ 0 & -1 & -1 & 0 \\ 0 & 1 & -1 & 0 \\ 0 & 0 & 0 & 0 \end{bmatrix} \quad (6)$$

We notice that with the ordering $\{|00\rangle, |10\rangle, |11\rangle, |01\rangle\}$, adopted for the basis vectors that span the four dimensional degenerate subspace of coding the quantum information, where the first qubit is the control and the second is the target, the U gate is a control $\pi/4$ -rotation. Introducing the control phase gate $P_\phi = \text{diag}(1, e^{i\phi}, 1, 1)$, we can construct the control-not gate with a control sign flip operation as $U_{CN} = P_\pi U^2$. Then the holonomic control not gate subjected to systematic errors is $U_{CN}(\delta) = U_{CN} + \delta P_\pi u$.

By means of the imperfect one and two qubit quantum gates so obtained by the optical model of holonomic computation [5], we can now proceed along the lines of [6], to provide an all optical physical implementation of the holonomic teleportation [8,9] and the holonomic remote gate construction [10,11], that have been put forward in [6], in the more mathematical framework of the CP^n model.

Finally we should mention that alternatives to the optical implementation of holonomies for quantum computation have been suggested recently [12], in a scheme that uses adiabatic manipulations of parameters determining the interaction between laser beams and trapped ions in order to generate abelian and non-abelian geometrical gates. In such a model in addition to the systematic control errors presented here one has to take in account other imperfection mechanisms such as interaction with the environment and the effect of the spontaneous atomic emission upon Berry connection, see e.g. [13].

-
- [1] P. Zanardi and M. Rasetti, Phys. Lett. A **264**, 94 (1999).
 - [2] J. Jones, V. Vedral, A. Ekert and G. Castagnoli, Nature **403**, 869 (1999).
 - [3] J. Pachos, P. Zanardi and M. Rasetti, Phys. Rev. A **61** 010305 (R) (2000).
 - [4] A. Shapere and F. Wilczek, "Geometric Phases in Physics", (World Scientific 1989).
 - [5] J. Pachos and S. Chountasis, Phys. Rev. A **62**, 052318 (2000).
 - [6] D. Ellinas and J. Pachos, "Universal Holonomic Quantum Computing and Imperfections", quant-ph/0009043, revised version to appear in Phys. Rev. A.
 - [7] J. Pachos, G. Morigi, W. Lange and H. Walther, to appear.
 - [8] D. Gottesman, in Proc. of the XXII Inter. Symp. on Group Theor. Methods in Physics, eds. S. P. Corney, R. Delbourgo and P. D. Jarvis, p. 32 (Cambridge, MA International Press), quant-ph/9807006.
 - [9] M. A. Nielsen and I. L. Chuang, "Quantum Computation and Quantum Information", (Cambridge Univ. Press, 2000).
 - [10] P. W. Shor, Proc. 35th Annual Symp. on Fundamentals of Computer Science (IEEE Press, Los Alamos, 1996) p. 56, quant-ph/9605011).
 - [11] X. Zhou, D. W. Leung and I. L. Chuang. "Quantum Logic Gate Constructions with one-bit "teleportation"", Phys. Rev. A **62**, 052316 (2000), quant-ph/0002039.
 - [12] L.-M. Duan, J. I. Cirac, and P. Zoller, Science 2001 June 1; 292: 1695.
 - [13] D. Ellinas, S. M. Barnett and M.-A. Dupertuis, Phys. Rev. A **39** 3228 (1989).